

# p/n K46020

### **Hall Effect Sender**


#### **General description**

P/n
Type: Hall Effect
Wave: Square
Imp/rev: 8 ppr
Voltage: 12/24V
Pull-up resistor: Internal

Thread: M22x1.5 Female Mech. Input: 8x3mm slot



#### **Electrical connection:**



### **Application**

- Speed sensor to drive a Speedo or Tachograph
- 2. RPM sensor off cam-shaft.



List Price \$87.50 +GST

## Accessories (extra)



X72221 8

Note: For accessories also see VDO Catalogue 9A page 74 Located at: www.vdo.net.au

#### **DRIVE KEYS**

Suitable for tacho and speedo generators, Hall-effect senders etc.

	Drive Keys			
A	Part No.	Dimension A	Dimension B	Dimension C
1	K72103	2.6 x 8mm	2.6mm	26mm
	230.061	3.0 x 8mm	3.0mm	28mm
	230.076	2.6 x 8mm	3.8mm	27mm
	230.062	2.6 x 8mm	Ø3.8mm	26mm
	230.063	2.6 x 8mm	Ø4.7mm	26mm
	230.064	2.6 x 8mm	Ø5.0mm	26mm
	230.065	2.6 x 8mm	Ø5.1mm	30mm
	K72113	2.6 x 8mm	Ø5.2mm	26mm

FA 21 Jan 2010